# **NMIS Chart**

- Overview
- Accessing a Basic Chart
- Building a Simple Custom Chart
- A More Compound Chart

Chart Considerations

 Creating or Editing a Chart
 Options

#### Add Dataset

#### **Overview**

The NMIS Chart is the base Component in opCharts, replicating each of the charts available natively in NMIS and providing the ability to create custom compound charts by combining multiple data sets, from any device, onto one chart component.

## Accessing a Basic Chart

opCharts automatically creates a chart for each and every metric being reported back to NMIS. These charts can be accessed from within the Node Details screen. Select Views -> Nodes from the opCharts menubar, then select a node from the list to open the Nodes Detail screen.

🐇 opCharts 3.2.4	Views - Reports - Ever	nts≖ Config≖							System -	Modules - Help -	🖌 🥝 EN 🗸	User: nmi:
Home Nodes	Home Nodes	View all nodes or sea a specific node or s nodes	rch for A View in map et of							Filter	Period 👻 🕻	;
Q Node Search	Monitored Services TopN Business Services	Nodes								i≣ Panel V	I Panel View	
Enter the Node N		Name -	Host	Links	Node Status	Group	Node Type	Role	Vendor	Location	Health	Last Update
Node Filter	Charts Dashboards Maps Manage Collectors View Polling Definitions Scheduled Outages	asgard	asgard.opmantek.com	• •	reachable	Open-	Open- router AudIT	core	Cisco Systems	default	99.545	
Current Filters						Audit						
Select a Filter		router1	bne-router1	U	unreachable	Brisbane	router	distribution	Systems	default	0.000	
Node Status		bne-	bne-server1	ଏ ବ୍ତ	degraded	egraded Brisbane	server	access	net-snmp	On Eris	90.971	
degraded		server1										
reachable		bne-	bne-switch1	U	0 degraded	Brisbane swit	switch	witch access	Cisco Systems	gc.dc	94.229	
unreachable	U	bnelab-ce1	10.248.0.11		reschable	bnelab	router	access	Cisco	default	92,601	
Customer	1	_		·					Systems			
Location Business Service		bnelab-ce2	10.248.0.12	U	reachable	bnelab	router	access	Cisco Systems	default	92.371	
Group	1	bnelab-ce3	10.248.0.13	U	reachable	bnelab	router	access	Cisco Systems	default	92.742	
Node Type	1	bnelab-ce4	10.248.0.14	U	degraded	bnelab	router	access	Cisco Systems	default	92.623	
Node Vendor	1	bnelab-p1	10.248.0.3	U	reachable	bnelab	router	access	Cisco Systems	default	94.083	
		bnelab-p2	10.248.0.4	U	reachable	bnelab	router	access	Cisco	default	93.629	

Any displayed chart can be added to a dashboard (existing or new) by clicking the drop down menu option Add to Dashboard button in the chart's title bar.



## **Building a Simple Custom Chart**

A good example of a Simple Custom Chart is the Overall Reachability, Availability, and Health chart. This chart is available in each node's Node Details screen, as shown below...



Notice how the expanded chart includes four separate metrics, all normalized into a percentage of use or availability. This normalization allows all four metrics to be displayed relative to each other without skewing the chart's scale or being forced to use the right-hand axis.

This chart, and others, can be used as-is, edited, or created from scratch.

### A More Compound Chart

For charts that include non-normalized data (i.e data with base values which are either very dynamic or are widely separated) you can use both the left AND right-hand vertical axis to define separate ranges. Please keep in mind that depending on the range(s) being display this can become visually deceiving.

# **Chart Considerations**

# **Creating or Editing a Chart**

1. A Chart must exist before it can be used or added to a Dashboard. To create a new Chart from scratch, Click the blue "+" icon from the Charts screen (Views -> Chart).

💰 opChar	ts 3.2.4	Views - Reports - Ever	nts - Config -	s	System <del>-</del>	Modules - Help - 🄇 EN - User: nmis -		
Home / Cha Charts 👔	arts	Home Nodes	Click the "+" icon to create a new chart.			Filter Period - 2		
		Interfaces						
+ 🗲	Monitored Services TopN				Search te	rm Name - Go X		
		Business Services		Description		Title		
0	prueba	Charts	access, edit and create					
0	00_grafic	Dashboards Maps	custom charts	Grafica que muestra los servicios de GMG		00_grafica_ins		
	Brisbane					Interface Average Bits		
0	CBQoS S	Manage Collectors View Polling Definitions				CBQoS Stack Test		
	CPU Loa	Scheduled Outages				CPU Load - IP		
	CPU Usage across multiple servers			Example of adapting				
	Charlotte WAN Link					WAN Link		
0	ClaroEC					Memoria Vs CPU		
	Critical CPU Load				Critical CPU Load			
0	GraficaCPUMeM					Memoria Vs CPU		
0	Internet Traffic IP					Internet Traffic IP		
	Key Perfe	ormance						

2. Assign your Chart a Name - This must be unique; no two Charts can have the same Chart Name. Chart names should also not include spaces or special characters.

3. You can also provide a Description of your Chart. This will be displayed on the Charts View page, and also when adding a Chart to a Dashboard.

### Options

**Graph Parameters - Period -** Defines the period of time represented in the Chart's horizontal axis. Accepted parameters are m=minute, h=hour, d=day. These parameters cannot be combined, if you want 1d and 2hs you must use 26h.

Graph Options - Title - This is what will be displayed in the Component window's title bar.

New Chart					
Name	Chart Name				
Description	Chart Description				
Graph Parameters					
Period	2d				
Graph Options					
Title	Chart Title				
Save Chart	Add Dataset C				

# Add Dataset

More information on this can be found HERE: Creating Charts with the opCharts Chart Editor