How to Bulk Edit device attributes

Bulk Editing Device Attributes

Open-AudIT makes it easy to edit the attributes of multiple devices at once.

The steps below outline the process (all images can be clicked to be enlarged).

View the Devices list.

You will need a role with Devices update permission.

You can select individual devices by clicking their check-boxes on the right side or selecting all devices in the Group by clicking the checkbox in the top right of the table (underneath the Edit button).

Once you have chosen your devices to edit, click the "Bulk Actions" button in the top right of the table.

				•
			≣ - 2 -	+ ₹ ?
			Search:	
▼	System Manufacturer 🍦	System OS Family	System Status	Bulk Actions
841- 25f), Support: right (c) piled Tue	Cisco Systems	Cisco IOS	production	
	Intel		production	
			production	

This will show you the Bulk Edit form. Any attributes you set on this form will be applied to all selected devices. You can set multiple attributes at once.

Set Attributes			
Asset Number	Ø	OS Bit	G
Attached System ID	Ø	OS Family	G
Class	~ Ø	OS Group	G
Cluster Name	ø	OS Installation Date	G
Cluster Type	C	OS Name	G
Comments	Ø	OS Version	G
Contact Name	ø	Owner	G
Description	Ø	Patch Panel	G
Dns Domain	Ø	Patch Panel Port	Ű
Dns Hostname	ß	Printer Color	G
Domain	ő	Purchase Amount	Ű
Environment	* ©	Purchase Cost Center	G
Form Factor	G	Purchase Date	C
FQDN	Ø	Purchase Invoice	G
Function	G	Purchase Order Number	G
Hostname	G	Purchase Service Contract Number	G
IP	۵ ۵	Purchase Vendor	G
Lease Expiry Date	G	Serial	C
Location	* Ø	Serial Imei	G
Location Latitude	¹⁰	Serial Sim	6

Click the icon to the right of the field you wish to edit. Change the field and click the green icon to submit.

You can also see at the bottom of the page a table showing the devices the changes will be applied to, and even run Discovery upon those devices.

Nmis Busir Nmis Poller Manage in Enterprise Organisatio	ness Service r Open-AudIT on			0 0 - 0 - 0	Warranty Duration Warranty Expires Warranty Type		8 8 8
Devices	Туре	Name	Domain	IP	Description	OS Family	Status
•	unknown	auto-152		192.168.88.152			production
۲	unclassified	auto-119		192.168.88.119			production
Open-AudiT Ente	emrise 3.0.0 is licensed to (Domantek for 12345 Norles - Cor	nmercial - Expires 18-9	en-2020			Powered by Comante
Open-AudIT Ente Purchase a licent	erprise 3.0.0 is licensed to 0 se for more nodes by clicki	Opmantek for 12345 Nodes - Cor ng here .	nmercial - Expires 18-S	ep-2020			Powered by Opma

That's it! You have just edited the attributes of as many devices as you need to.

There is absolutely no need to manually edit each individual device 🙂

NOTE Bulk edit selections won't stay selected after clicking next page

If this occurs then the issue you're seeing is related to the table control being used on the webpage. It only stores in memory the state of the check boxes for the current page being viewed. If you make selections, then page forward/back those selections will be lost. You can, however, accomplish what you want by expanding the number of devices shown on each page. In the top-left corner is a drop-down labeled "records per page"; use this to expand the number of entries displayed until you see all you want to select for Bulk Edit.

Devi	ces	3
50	-	records per page